



DIGITAL INVERTER GENERATORS

POWER YOU CAN DEPEND ON

Ideal for the contractor on the go or outdoorsy weekend warrior – Milbank's digital inverters provide reliable, quiet and clean energy for all sensitive electronic needs. The 4-cycle gasoline-powered inverters provide two 120V, AC outlets.



1000W | MPG1000I



1800W | MPG2000IP


Note: Running engines give off carbon monoxide, an odorless, colorless, poison gas so it is important to keep exhaust gas away from any windows, doors, ventilation intakes or crawl spaces. Carbon monoxide detectors must be installed and maintained in your home. Milbank reserves the right to make changes in specifications and features shown without notice or discontinue the product described at any time without notice or obligation.



DIGITAL INVERTER GENERATORS

FEATURES

- Asymmetrical Fans
- Dual Muffler Design
- Double Insulated Acoustic Hood
- Yellow Color-Coded Touch points
- Power Indicator Light
- AC Overload Reset
- High Efficiency Run Mode
- Low Oil Shut Down
- Light Weight, Ergonomically Designed
 - 1000W – 30 lbs.
 - 1800W – 43 lbs.
- Sound Output, 53-59 dba NL/FL
- Less Than 3% Total Harmonic Distortion (THD)
- Tool Kit and Oil Bottle Included



PARALLEL CORD | INVPCORD1

SPECIFICATIONS

Model Number	MPG1000I	MPG2000IP
ENGINE		
Displacement	52cc	79cc
Low Oil Shut Down	Yes	Yes
Electric Start (with battery)	No	No
Automatic Fuel Shut-Off	No	No
CARB Compliant Available	Yes	Yes
OUTPUT		
Running Watts	1000	1800
Starting Watts	1100	2200
ADDITIONAL PERFORMANCE CHARACTERISTICS		
Run Time @ 1/2 load	9 hrs	11 hrs
Sound Rating	at 25% load	53 dbA
	at 50% load	56 dbA
Parallel Capable	No	Yes (Model #INVPCORD1)
ALTERNATOR		
Rotor Windings	Cu	Cu
CONTROL PANEL RECEPTACLES		
NEMA 5-15R (125VAC 20A Duplex)	Qty = 2	Qty = 2
NEMA 5-20R (125VAC 20A Duplex)	Qty = 0	Qty = 0
20 Amp push button circuit breakers	Qty = 0	Qty = 0
NEMA L14-30R (125/250VAC 30A Twist Lock)	Qty = 0	Qty = 0
2 Pole Toggle-Type Main Line Breaker	8.3 / 9.1 amps	15 / 18.3 amps
12V DC Outlet	No	Yes
ACCESSORIES		
Oil Bottle (1 bottle sized for engine: SAE 10W30)	No	Yes
Oil Funnel	Yes	Yes
Multi Outlet 25' Power Cord	No	No
SHIPPING INFORMATION		
Weight	30 lbs	43 lbs

2 YEAR WARRANTY

Note: Running engines give off carbon monoxide, an odorless, colorless, poison gas so it is important to keep exhaust gas away from any windows, doors, ventilation intakes or crawl spaces. Carbon monoxide detectors must be installed and maintained in your home. Milbank reserves the right to make changes in specifications and features shown without notice or discontinue the product described at any time without notice or obligation.