



**MILBANK**<sup>®</sup>  
ENERGY AT WORK

# MANUAL TRANSFER SWITCH 30 & 50A POWER INLET BOXES

The 30 and 50A power inlet boxes pair with several models of Milbank's manual transfer switch; allowing for easy power transfer to and from the generator.

## 30A Power Inlet Box | MMTSINLET30



The MMTSINLET30 is included in the following manual transfer switch packages:  
MMTS301SYSX  
MMTS301SYSX1C  
MMTS301SYSX2C



## SPECIFICATIONS

Model Number	MMTSINLET30	MMTSINLET50
Warranty	4 Years	4 Years
<b>RECEPTACLE</b>		
Amperage	30	50
Mounting	Flanged	Flanged
Voltage	125/250 AC	125/250 AC
Dielectric Voltage Withstand	2000V	2000V
Poles	3	3
Wire	4, Grounding	4, Grounding
Type	Receptacle, Inlet, Grounding	Receptacle, Inlet, Grounding
NEMA Configuration	L14-30	CS6375
UL Certification	Yes	Yes
CSA Certification	Yes	Yes
<b>ENCLOSURE</b>		
Type	NEMA 3R	NEMA 3R
Material	Powder Coated, 16 Gauge Steel	Powder Coated, 16 Gauge Steel
Knockouts	(2) 1/2" - 3/4"	(2) 1/2" - 3/4"
Mounting Embosses	3, Standard	3, Standard

## 50A Power Inlet Box | MMTSINLET50



The MMTSINLET50 is included in the following manual transfer switch packages:  
MMTS501SYSX  
MMTS501SYSX1C  
MMTS501SYSX2C



**4** YEAR WARRANTY