

## The **EB2200i** Industrial Generator From Honda



2200 watts of quiet, lightweight, portable jobsite power for running and recharging tools. It's designed to meet OSHA requirements and features a 120V GFCI duplex receptacle. **New CO-MINDER™ advanced carbon monoxide detection system** continuously measures CO levels and automatically shuts down the generator before detected CO levels near the generator become dangerously high.\*

### FEATURES


- **2200 watts** (18.3 A) of Honda Inverter 120V AC Power
- **GFCI, neutral bond** for OSHA regulated sites
- **Super quiet**, only 48 to 57 dB(A)
- **Light weight (less than 48 lbs.)** makes transporting easy
- **Fuel efficient**, runs up to 8.1 hours on 0.95 gallons of fuel
- **CO-MINDER™** automatically shuts down the generator if it detects carbon monoxide gas reaching unsafe levels
- **Advanced inverter technology** provides reliable power to computers and other sensitive equipment
- **Fuel-Off switch** allows the carburetor to run dry, reducing the effects of fuel deterioration and helps short and mid-term storage
- **Oil Alert®, Overload Alarm** and **Eco Throttle®**
- **USDA-qualified spark arrestor/muffler**
- **Honda 3-Year Residential Warranty/ Honda 3-Year Commercial Warranty†**



### SPECIFICATIONS

### EB2200i

Engine	Honda GXR120
Displacement	121cc
Max AC Output	2200w max. 120V (18.3A)
Rated AC Output	1800w rated (15A)
Receptacles	20A 125V GFCI Duplex
Frequency Regulation	Inverter
Starting System	Recoil
Fuel Tank Capacity	.95 gal
Run Time Per Tankful	3.2 hours at rated load 8.1 hours at 1/4 load
Noise Level**	57 dB(A) at rated load 48 dB(A) at 1/4 load
Dimensions (L x W x H)	20.0" x 11.4" x 16.7"
Dry Weight	47.4 lbs.
USDA Spark Arrestor	Standard
CO-MINDER™	Standard



Find out more at [gen.honda.com](http://gen.honda.com).

\*This product complies with the ANSI/PGMA G300-2018 standard. †Warranty applies to all Honda GX Series Engines and GX Series-powered Honda Power Equipment, 100cc or larger, purchased or put into rental service since January 1, 2010. Exceptions apply. See full warranty details at [honda.com](http://honda.com). Does not apply to EU1000 models. \*\*Tested in accordance with ISO 9614-2, sound pressure level calculated at 23 Feet (7 meters) using the front plane of the generator (control panel side) per ASHRAE Handbook 2017. Please read the owner's manual before operating your Honda Power Equipment and never use in a closed or partly enclosed area where you could be exposed to odorless, poisonous carbon monoxide. Connection of a generator to house power requires a transfer device to avoid possible injury to power company personnel. Consult a qualified electrician. © 2020 American Honda Motor Co., Inc. C1025