

CX Series

Portable Generators

Powermate



Power. When you need it.

CX Series

Portable Generators

Portable power **WHEN
AND WHERE** you need it.





Trust in the portable power of Powermate's CX Series generators.

Featuring extended run times and sturdy framework for stable mobility, the CX Series portable generators are ideal for a variety of occasions:

- Camping
- Tailgating
- Emergency home backup

With electric start capabilities on select models, CX Series portable generators are easy to power up, and their compact design takes up minimal storage space.



CX Series

Portable Generators

Innovative features provide protection and ensure years of reliability.

Folding handles

(all models except CX1400)

For simple storage and transportation



Low oil shutdown

Monitors the oil level to prevent product damage



Digital multi meter

Tracks engine runtime for required maintenance

Powermate OHV engine

Provides consistent power for various applications



Covered outlets

Protect against the elements, dust and debris

Never-flat wheels

Easily travel over rough terrain



CX Series

Portable Generators



Specifications

Series	CX1400	CX3500	CX5500	CX6500E	CX8000E
Model Number	PC0141400 (49 ST/CSA)	PC0143500 (49-State/CSA) PMC143500 (CARB)	PC0145500 (CSA) PMC145500 (49-State/CARB)	PC0146500 (49-State/CSA)	10000001785 (49-State)
Running Watts	1400	3500	5500	6500	8000
Starting Watts	1700	4375	6875	8125	10000
Engine Displacement	98cc	208cc	420cc	420cc	445cc
Engine Type	OHV	OHV	OHV	OHV	OHV
Starting Method	Recoil Pull Start	Recoil Pull Start	Recoil Pull Start	Electric/Recoil Pull Start	Electric/Recoil Pull Start
Battery	N/A	N/A	N/A	Included	Included
Low Oil Shutdown	Yes	Yes	Yes	Yes	Yes
Fuel Tank Capacity (Gallons)	1.5	4.5	7.0	7.0	7.0
Run Time @ 50% Load	8.5 Hours	12 Hours	12.5 Hours	9.75 Hours	9.4 Hours
Hour Meter	Yes	Yes	Yes	Yes	Yes
Outlets	(1) 120V 20A 5-20R Duplex (1) 12V DC	(1) 120V 20A 5-20R Duplex (1) 120V 30A L5-30R Twist Lock (1) 120V 30A TT-30R (RV Ready)	(2) 120V 20A 5-20R Duplex (CSA only) (2) 120V 20A 5-20R GFCI Duplex (49-State/CARB only) (1) 120/240V 30A L14- 30R Twist Lock	(2) 120V 20A 5-20R GFCI Duplex (1) 120/240V 30A L14-30R Twist Lock	(2) 120V 20A 5-20R GFCI Duplex (1) 120V 30A L5-30R Twist Lock (1) 120/240V 30A L14-30R Twist Lock
Covered Outlets	Yes	Yes	Yes	Yes	Yes
Handle Style	N/A	Folding/Locking	Dual Folding/Locking	Dual Folding/Locking	Dual Folding/Locking
Wheel Type	N/A	8" Never Flat	12" Never Flat	12" Never Flat	12" Never Flat
Dimensions (L" x W" x H")	19.8 x 15.6 x 15.9	25.6 x 23.8 x 21.6	31.5 x 27.6 x 22	31.5 x 27.6 x 24.5	31.5 x 27.6 x 24.5
Product Weight (lbs)	60	107	173	202	219
Warranty - Residential	2 Year Limited	2 Year Limited	2 Year Limited	2 Year Limited	2 Year Limited
Warranty - Commercial	1 Year Limited	1 Year Limited	1 Year Limited	1 Year Limited	1 Year Limited

How much **POWER** do you need?

Sizing a portable generator is easy. Check out this sample:

- 1 Choose which devices you want to power at the same time.
- 2 Record and add the running watts listed for each device that you need to power.
- 3 Record the starting watts listed for each device.
- 4 Select the one device with the highest starting watts. Add that number to the total running watts to determine the total wattage requirement.

Device	Running watts	Additional starting watts	GENERATOR SIZE Minimum starting watts for your needs  5250 starting watts
Refrigerator	700	2200	
Sump Pump	1050	2150	
Microwave	1000		
Lights	300		
TOTAL	3050	+ 2200	=

Powermate.com

Powermate, LLC
S45 W29290 Hwy. 59, Waukesha, WI 53189
1-800-445-1805