



DXGN14000

FEATURES:

- ✓ Engine – Honda GX630
- ✓ Fuel Type – Gasoline
- ✓ AC Voltage – 120V/ 240V
- ✓ AC Frequency – 60 Hz
- ✓ Premium Alternator with less than 6% Harmonic Distortion
- ✓ Includes Lifting Kit & Wheel Kit (Battery included)
- ✓ 3 Year Engine Warranty

POWERED by **HONDA**



Photo is representative only



PRAMAC America LLC • 888-977-2622 (888-9-PRAMAC) • WWW.PRAMAC.COM • usa@pramac.com

RATINGS

Rated/ Surge Watts	11700/ 14000
Frequency - Voltage	60hz - 120/240V

ENGINE

Engine Model	Honda GX630
Fuel Type	Gasoline
Starting	Electric
Certifications	50 State and CSA
Engine Displacement	688cc
Oil Alert	Yes
USDA Spark Arrestor	Yes
Noise Level @ 22 ft	82.7 dBA

FUEL

Fuel Tank Capacity	10.0 gal
Fuel Gauge	Yes
Run Time @50% Load	7.8 hours

DIMENSIONS & WEIGHT

L x W x H	37.5 x 24.3 x 31.1 in
Dry Weight	346 lbs

OUTLET

(2) 120V 5-20R GFCI Duplex	(1) 14-50R, 120/240V
(1) L14-30R, 120/240V	

EAN: 8018539 06299 6