

DEWALT®

DXGN7200

FEATURES:

- ✓ Engine – Honda GX390
- ✓ Fuel Type – Gasoline
- ✓ AC Voltage – 120V/ 240V
- ✓ AC Frequency – 60 Hz
- ✓ Premium Alternator with less than 6% Harmonic Distortion
- ✓ Includes Integrated Lifting Kit
- ✓ Optional Wheel Kit and Battery Available
- ✓ 3 Year Engine Warranty

POWERED by
HONDA



Photo is representative only



shown with optional wheel kit

RATINGS

| | |
|--------------------|------------|
| Rated/ Surge Watts | 6100/ 7200 |
|--------------------|------------|

| | |
|---------------------|-----------------|
| Frequency - Voltage | 60hz - 120/240V |
|---------------------|-----------------|

ENGINE

| | |
|--------------|-------------|
| Engine Model | Honda GX390 |
|--------------|-------------|

| | |
|-----------|----------|
| Fuel Type | Gasoline |
|-----------|----------|

| | |
|----------|------------------|
| Starting | Recoil /Electric |
|----------|------------------|

| | |
|----------------|------------------|
| Certifications | 50 State and CSA |
|----------------|------------------|

| | |
|---------------------|-------|
| Engine Displacement | 389cc |
|---------------------|-------|

| | |
|-----------|-----|
| Oil Alert | Yes |
|-----------|-----|

| | |
|---------------------|-----|
| USDA Spark Arrestor | Yes |
|---------------------|-----|

| | |
|---------------------|--------|
| Noise Level @ 22 ft | 79 dBA |
|---------------------|--------|

FUEL

| | |
|--------------------|---------|
| Fuel Tank Capacity | 8.0 gal |
|--------------------|---------|

| | |
|------------|-----|
| Fuel Gauge | Yes |
|------------|-----|

| | |
|--------------------|----------|
| Run Time @50% Load | 13 hours |
|--------------------|----------|


DIMENSIONS & WEIGHT

| | |
|-----------|-----------------------|
| L x W x H | 31.4 x 22.3 x 26.3 in |
|-----------|-----------------------|

| | |
|------------|---------|
| Dry Weight | 206 lbs |
|------------|---------|

OUTLET

| | |
|--|---|
|  (2) 120V 5-20R GFCI Duplex |  (1) 120V L5-30R |
|--|---|

| |
|---|
|  (1) L14-30R, 120/240V |
|---|

PRAMAC America LLC • 888-977-2622 (888-9-PRAMAC) • WWW.PRAMAC.COM • usa@pramac.com

EAN: 8018539 06298 9