

S7200

Generators



FEATURES:

- ✓ Long Run Time
- ✓ Voltage Selector Switch
- ✓ Idle Control
- ✓ < 6% Harmonic Distortion
- ✓ Fuel Gauge
- ✓ Tool Storage Box
- ✓ Optional Portability Kit (No flat tires)
- ✓ 2 Year Warranty (3 Year Engine)
- ✓ Hour Meter
- ✓ Easy Access Fuel Valve



RATINGS	
Rated/ Surge Watts	6100/ 7200
Frequency - Voltage	60hz - 120/240V
ENGINE	
Engine Model	Honda GX390
Fuel Type	Gasoline
Starting	Electric/ Recoil Start
Certifications	CARB & CSA
Engine Displacement	389cc
Oil Alert	Yes
USDA Spark Arrester	Yes
Noise Level @ 22 ft	75 dBA
FUEL	
Fuel Tank Capacity	8.0 gal
Fuel Gauge	Yes
Run Time @ 75% Load	10 hours
DIMENSIONS & WEIGHT	
L x W x H	31.38x22.25x26.25 in
Dry Weight	199 lbs
OUTLET	
(2) 5-20R 120V 20A DUPLEX GFCI (1) L5-30R 120V 30A TL	
(1) L14-30R 120V/240V 30A TL	