



POWERING YOUR *life.*

Model 201183

UPC 817198025896

Warranty 3 Years

2500
STARTING WATTS
Propane: 2500

1850
RUNNING WATTS
Propane: 1665

RUN TIME 11.5 hrs. **RUN TIME** 34 hrs. **NOISE LEVEL** 53 dBA



EZ START DIAL
Confusion free **ENGINE START-UP**



ULTRA QUIET
LOW NOISE - high performance



LIGHTWEIGHT
Compact design weighs **LESS THAN 40 LB.**



PARALLEL READY
Link 2 units for **DOUBLE POWER**

Receptacles



20 AMP
120V, 5-20R



Parallel



12V DC
Regulated Automotive

Specifications

START TYPE	Recoil
VOLTAGE (V) AC	120
DC VOLTS	12
ENGINE SIZE (cc)	79
FUEL TYPE	Gasoline or Propane
GASOLINE CAPACITY (gal.)	1.1
OIL TYPE	10W-30
OIL CAPACITY (fl. oz./mL)	16.9/500
LOW OIL SHUT-OFF	Yes
EMISSIONS	EPA III/CARB



**CARBON MONOXIDE
AUTO-SHUTOFF SYSTEM**



Our 2500-watt inverter is one of the lightest in the industry and features CO Shield® carbon monoxide auto shutoff system. The Dual Fuel feature allows the 79cc engine to run on gasoline or propane. Enjoy the quiet 53 dBA for up to 11.5 hours on gasoline or up to 34 hours with a 20-lb propane tank and increase your power with the optional Parallel Kit.

Inside the box

GENERATOR
PROPANE HOSE 2.3 FT.
USB ADAPTER

OPERATOR'S MANUAL
OIL FUNNEL
ENGINE OIL

What You Need

GASOLINE OR PROPANE

*Specifications, descriptions and illustrations are subject to change without notice.



PACKAGE (gross)
Weight: 46.1 lb.
Size: 20.1 x 13.4 x 19.1 in.



PRODUCT (net)
Weight: 39 lb.
Size: 17.3 x 12 x 17.7 in.

CHAMPION POWER EQUIPMENT, INC.
12039 Smith Ave., Santa Fe Springs, CA 90670, USA
www.championpowerequipment.com