

POWERING YOUR *life.*

Model 100306

UPC 817198020426

Warranty 3 Years

2000
STARTING WATTS

1600
RUNNING WATTS

RUN TIME 11 hrs.

NOISE LEVEL 53 dBA



EZ START DIAL

Confusion free **ENGINE START-UP**



DIGITAL LED DISPLAY

Output, run time, fuel life and level



CLEAN ELECTRICITY

Power **SENSITIVE ELECTRONICS**



COLD START

Easy starts in **COLD WEATHER**



PARALLEL READY


Link 2 units for **DOUBLE POWER**

PARALINK

Receptacles



12V DC
Automotive



20 AMP
120V, 5-20R

Specifications

START TYPE	Recoil
VOLTAGE (V)	120
ENGINE SIZE (cc)	80
FUEL TYPE	Gasoline
GASOLINE CAPACITY (gal.)	1.1
OIL TYPE	10W-30
OIL CAPACITY (qt.)	0.4
LOW OIL SHUT-OFF	Yes
EMISSIONS	EPA



Lightweight power and clever design are yours with the Champion 2000-watt stackable inverter generator. Rely on the 80cc engine and enjoy a quiet 53 dBA for up to 11 hours of run time. The optional ParaLINK Parallel Kit with RV Ready outlet and 30 amps of power doubles your output and saves space.

Inside the box

GENERATOR
OPERATOR'S MANUAL
OIL FUNNEL

12V USB ADAPTER

What You Need

GASOLINE
ENGINE OIL (10W-30)

*Specifications, descriptions and illustrations are subject to change without notice.



RETAIL PACKAGE (gross)
Weight: 53.4 lb.
Size: 22.4 × 14.4 × 18.1 in.



PRODUCT (net)
Weight: 46.3 lb.
Size: 20.5 × 12.6 × 16.9 in.

CHAMPION POWER EQUIPMENT, INC.
12039 Smith Ave., Santa Fe Springs, CA 90670, USA
www.championpowerequipment.com – Made In China