## W03081 3000 Watt Recoil Start Generator

## FIRMAN®



## **FEATURES & BENEFITS:**

- The FIRMAN OHV engine (Max-Pro Series) for longer life, higher performance and lower maintenance
- Phoenix Fat Head Block and FIRMAN PowerStream Alternator
- High leverage single folding handle with grip for easy maneuver
- Quiet muffler (Whisper Series) with USDA FS certified spark arrester
- Automatic Voltage Regulator VS (Voltage-Compensator) series
- Durable compact integrated design
- 4 in 1 Data-Minder monitor Volts, Hz, Hours and low oil
- Color coded control touch points



















Model	W03081
Running Watts	3000
Starting Watts	3300
Engine Displacement	171cc
Voltage - Frequency	120 VAC– 60Hz
Noise Level (23 ft) @ 1/4 Load	58 dB
Fuel Tank Capacity	1.8 Gallons
Run Time @ 50% Load	12 Hours
Dry Weight	94.8 lbs.
Shipping Dimensions (LxWxH)	28.5"X20.2X19.3"
Warranty	3 years